





1.	DIGITAL MIXER PreSonus StudioLive16.4.2 AI	SPECIFICATION																																																												
	 	<table border="0"> <tr> <td>Type</td> <td>Digital</td> </tr> <tr> <td>Channels</td> <td>16</td> </tr> <tr> <td>Inputs - Mic Preamps</td> <td>16 x XLR</td> </tr> <tr> <td>Inputs - Line</td> <td>16 x 1/4", 2 x RCA (Tape)</td> </tr> <tr> <td>Inputs - Other</td> <td>2 x stereo aux returns, 1x talkback mic</td> </tr> <tr> <td>Inputs - Digital</td> <td>32 x digital returns from computer</td> </tr> <tr> <td>Outputs - Main</td> <td>2 x XLR, 1 x XLR (Mono)</td> </tr> <tr> <td>Outputs - Direct</td> <td>2 x DB25</td> </tr> <tr> <td>Outputs - Other</td> <td>2 x 1/4" (CR), 4 x 1/4" (Subgroup)</td> </tr> <tr> <td>Outputs - Digital</td> <td>1 x S/PDIF</td> </tr> <tr> <td>Headphones</td> <td>1 x 1/4"</td> </tr> <tr> <td>Send/Return I/O</td> <td>4 x 1/4" (Aux In), 10 x 1/4" (Aux Out)</td> </tr> <tr> <td>Data I/O</td> <td>FireWire 800, Thunderbolt and Dante optional</td> </tr> <tr> <td>I/O Expansion Slots</td> <td>1, filled w/ FireWire 800 / S/PDIF card</td> </tr> <tr> <td>Phantom Power</td> <td>Yes</td> </tr> <tr> <td>EQ Bands</td> <td>Channel: 4-band Semi-parametric; Main: 31-band Graphic</td> </tr> <tr> <td>Aux Sends</td> <td>6 x Pre/Post + 4 x internal FX</td> </tr> <tr> <td>Busses/Groups</td> <td>4 Bus</td> </tr> <tr> <td>Faders</td> <td>21 x 100mm</td> </tr> <tr> <td>Channel Inserts</td> <td>Yes (CH 1-32)</td> </tr> <tr> <td>Effects</td> <td>Yes</td> </tr> <tr> <td>Talkback</td> <td>Yes</td> </tr> <tr> <td>Transport Controls</td> <td>No</td> </tr> <tr> <td>DAW Control</td> <td>No</td> </tr> <tr> <td>Computer Connectivity</td> <td>2 x FireWire 800</td> </tr> <tr> <td>Rackmountable</td> <td>Yes (14 spaces, rack ears included)</td> </tr> <tr> <td>Length</td> <td>22.35 "</td> </tr> <tr> <td>Width</td> <td>17.22 "</td> </tr> <tr> <td>Depth</td> <td>6.9 "</td> </tr> <tr> <td>Weight</td> <td>10.43 kg</td> </tr> </table>	Type	Digital	Channels	16	Inputs - Mic Preamps	16 x XLR	Inputs - Line	16 x 1/4", 2 x RCA (Tape)	Inputs - Other	2 x stereo aux returns, 1x talkback mic	Inputs - Digital	32 x digital returns from computer	Outputs - Main	2 x XLR, 1 x XLR (Mono)	Outputs - Direct	2 x DB25	Outputs - Other	2 x 1/4" (CR), 4 x 1/4" (Subgroup)	Outputs - Digital	1 x S/PDIF	Headphones	1 x 1/4"	Send/Return I/O	4 x 1/4" (Aux In), 10 x 1/4" (Aux Out)	Data I/O	FireWire 800, Thunderbolt and Dante optional	I/O Expansion Slots	1, filled w/ FireWire 800 / S/PDIF card	Phantom Power	Yes	EQ Bands	Channel: 4-band Semi-parametric; Main: 31-band Graphic	Aux Sends	6 x Pre/Post + 4 x internal FX	Busses/Groups	4 Bus	Faders	21 x 100mm	Channel Inserts	Yes (CH 1-32)	Effects	Yes	Talkback	Yes	Transport Controls	No	DAW Control	No	Computer Connectivity	2 x FireWire 800	Rackmountable	Yes (14 spaces, rack ears included)	Length	22.35 "	Width	17.22 "	Depth	6.9 "	Weight	10.43 kg
Type	Digital																																																													
Channels	16																																																													
Inputs - Mic Preamps	16 x XLR																																																													
Inputs - Line	16 x 1/4", 2 x RCA (Tape)																																																													
Inputs - Other	2 x stereo aux returns, 1x talkback mic																																																													
Inputs - Digital	32 x digital returns from computer																																																													
Outputs - Main	2 x XLR, 1 x XLR (Mono)																																																													
Outputs - Direct	2 x DB25																																																													
Outputs - Other	2 x 1/4" (CR), 4 x 1/4" (Subgroup)																																																													
Outputs - Digital	1 x S/PDIF																																																													
Headphones	1 x 1/4"																																																													
Send/Return I/O	4 x 1/4" (Aux In), 10 x 1/4" (Aux Out)																																																													
Data I/O	FireWire 800, Thunderbolt and Dante optional																																																													
I/O Expansion Slots	1, filled w/ FireWire 800 / S/PDIF card																																																													
Phantom Power	Yes																																																													
EQ Bands	Channel: 4-band Semi-parametric; Main: 31-band Graphic																																																													
Aux Sends	6 x Pre/Post + 4 x internal FX																																																													
Busses/Groups	4 Bus																																																													
Faders	21 x 100mm																																																													
Channel Inserts	Yes (CH 1-32)																																																													
Effects	Yes																																																													
Talkback	Yes																																																													
Transport Controls	No																																																													
DAW Control	No																																																													
Computer Connectivity	2 x FireWire 800																																																													
Rackmountable	Yes (14 spaces, rack ears included)																																																													
Length	22.35 "																																																													
Width	17.22 "																																																													
Depth	6.9 "																																																													
Weight	10.43 kg																																																													

2.	ACTIVE SPEAKER -TWO-WAY SYSTEM RCF HD 32-A	SPECIFICATION
		<p>ACOUSTICAL SPECIFICATION</p> <p>Frequency response 45 Hz- 20 KHz Max SPL 131 dB Horizontal coverage angle 90° Vertical coverage angle 60° Compression driver 2.0" neo, 3" voice coil Midrange - Woofer 12", 2.5" voice coil</p> <p>INPUT SECTION</p> <p>Input signal (Impedance): bal/unbal Input/Output connector xlr-jack Input sensitivity +2 dBu / + 4dbu</p> <p>PROCESSOR SECTION</p> <p>Crossover frequencies 800 Hz Protections Themel, RMS Sensitivity control Yes Limiter soft limiter High Pass - Controls Volume, EQ, shape, Mic/Line</p> <p>AMPLIFIER</p> <p>Power Supply Switching 700 watt High Frequencies D / 200 watt Mid Frequencies - Low Frequencies D / 500 watt Cooling Convention Connection Powercon In/Out</p> <p>PHYSICAL</p> <p>Height: 647 mm (25.47") Width: 380 mm (14.96") Depth: 380 mm (14.96") Weight 34 kg</p>

4.	POWER CONDITIONER Furman PL- 8CE	SPECIFICATION
		<p>Maximum Output Current: 10 amps</p> <p>Line Cord: 3/1.0MM AWG, 2.5M cord w/IEC female to 10A Schuko plug</p> <p>Pull-out Lights Two multi-LED, dimmable lamps</p> <p>BNC Socket w/Switch Rear rack lamp, 12VAC 500MA maxx (lamp not included)</p> <p>Operating Voltage 180 to 274 VAC</p> <p>Spike Protection Mode Line to neutral, zero ground leakage</p> <p>Spike Clamping Voltage 375 VAC peak @ 3,000 Amps</p> <p>Response Time 1 nanosecond</p> <p>Maximum Surge Current 6,500 Amps</p> <p>Noise Attenuation 10 dB @ 10 kHz, 40 dB @ 100 kHz, 50 dB @ 500 kHz</p> <p>Dimensions 482.6mm W x 266.7mm D x 44.5mm H</p> <p>Weight 6 kg</p> <p>Power Consumption 12 watts</p> <p>Safety Listing CE</p>

5.	SPEAKER STAND K&M 21436	SPECIFICATION	
		Height	From 1,320 to 2,020 mm
		Height Adjustment	Locking screw with push button system
		Leg Construction	Tube legs with cross braces
		Material	Aluminum
		Max. Load Capacity	40 kg
		Product category	Baseline
		Rod Combination	2-piece folding design
		Special Features	Patented gradual height adjustment system, integrated shock absorber, mounting aid include
		Tube end(s)	Diameter 35 mm
		Type	Black
Weight	3.41 kg		